SOLUS UHCRa™ Activation and Software Upgrade Instructions

This document provides instructions for connecting, activating and upgrading a SOLUS Ultra[™] scan tool using ScanBay.

Programming Time

Estimated Platform Activation Time: 2 minutes

To speed new platform activation, make sure to perform a ScanBay Truck Stock upgrade at the time of a new software release.

Software Upgrade Estimated Time: 11 minutes

Includes connect to PC, ScanBay programming, unit restart and installation/loading.

Before You Begin

To perform the activation and software upgrade, you need the following:

- SOLUS Ultra unit with fully charged battery
- Mini USB Cable
- The SOLUS Ultra AC/DC power supply
- Access to AC power
- ScanBay installed on a PC

Activating and Upgrading a SOLUS Ultra Scan Tool

Use the procedure below to activate and upgrade a SOLUS Ultra with ScanBay:

To activate and upgrade a SOLUS Ultra diagnostic tool:

- Connect an AC/DC power supply to the SOLUS Ultra diagnostic tool. The SOLUS Ultra scan tool automatically powers up when connected to a power source.
- 2. From the SOLUS Ultra Home screen, select **Tools** > **Connect-to-PC** (Figure 1).



Figure 1 Sample SOLUS Ultra Home screen

- 3. When the Connect-to-PC message displays (Figure 2), attach the USB cable as follows:
 - a. Connect the large end of the mini USB cable to a USB port on your PC.
 - b. Connect the small end of the cable to the mini USB port on top of the tool (Figure 3).

Tool	s and Setup		11:09
÷ A			¢
Connect-to-P(C		
	SOLUS Ultra™ of for use with progra	can be connected to a PC as a Mass Storage I ams like ShopStream Connect and Windows E	Device ixplorer.
		Continue	-100
	8	Exit	

Figure 2 Sample SOLUS Ultra Connect to PC message



Figure 3 Sample SOLUS Ultra mini USB port location

4. Once the USB cable is connected, select Continue on the SOLUS Ultra unit.

A communication link is established between the scan tool and the computer, and the SOLUS Ultra screen updates to indicate the connection is active (Figure 4).

Tools and Setup		11:09
æ 🙃		¢
Connect-to-PC		
	Scanner is now in Connect-to-PC mode.	
	Press X to exit.	
	E-14	-
	EXIL	

Figure 4 Sample SOLUS Ultra active PC connection message

5. Open an invoice for your customer and click the **ScanBay** button.

The Select Programming Media dialog box displays (Figure 5).

Select Programming Media	(DSS ScanBay Version 10.4.0.7)
Step 1 Select Product	Inventory Credits On Hand 0
	Consignments Remaining 6
© SOLUS™, MODIS (©ETHOS®, SOLUS © VERUS® or VERD Insert Compacti Help What's New? Inven	™ or Vantage PRO™ – CompactFlash® PRO™ or SOLUS Ultra™) NCT™ Flash® to Continue

Figure 5 Sample ScanBay Select Programming Media dialog box

- 6. Select the menu item with SOLUS Ultra in the dialog box, then click Next.
- 7. Continue selecting **Next** until the "Select Qualifying Software" screen displays.
- 8. Click to highlight the radio button for the desired software upgrade, then select Next.

- 9. Follow the screen prompts and select Next as needed to begin programming.
- 10. When the process completed message displays select **Finish**, exit ScanBay, and disconnect the USB cable from the SOLUS Ultra unit.

Step 12.Complete!	SOLUS Ultra Credits On Hand N/A
C. P. LEVERT DECISION	Consignments Remaining 0
Process Completed.	
Select "Finish" to return to DSS.	

Figure 6 Sample process completed message

The software update has now been downloaded to the scan tool, but is not yet installed.

11. On the SOLUS Ultra select **Exit** to close Connect-to-PC mode, which begins the installation of the new software.

Once the installation process is complete the SLOLUS Ultra Home screen displays and the unit is ready for use.